#### PICTURE PERFECT SOUND®







LS15-HzUMB-33UT

## **Completed Assembly**



# **Universal TV** Mount Hardware

8 x

M6 Screw



8 x M8 Screw



Spacers

12 x



1 x Foam Tape



2 x Short Button

Head Screw

**HzUMB** Parts



Long Button Head Screw





2 x Swing Arm Adjustable Upright



4 x M6 Lock Washer



4 x M8 Lock Washer

4 x Flat Washer

2 x Hex Key



2 x









Loosen set screws on **Adjustable Uprights**. Slide **Adjustable Uprights** to align with TV mount holes.



Affix Adjustable Uprights and TV Mount Rails with M6 or M8 Screws and Washers. Use Spacers as needed to ensure the Adjustable Uprights and TV Mount Rails are level.



(A) TV is thinner than speaker



(B) TV is thicker than speaker



Loosely attach **Swing Arms** to **Paddles** and **Adjustable Uprights** using **Long Button Head Screws**. Typically, **Paddles** will be oriented as shown in (A), but may be turned sideways for thicker TVs as shown in (B).







Position the speaker along the TV's edge so the **Paddles** rest on the speaker's mount rails. Align T-nuts in the mount rails with holes on **Paddles**. Tighten the **Long Button Head Screws** with extra torque. (Mount rails and T-nuts come attached to back of speaker.)



Slide speaker flush and centered with TV. Screw **Paddles** to sliding T-nut in speaker's mount rails using **Short Button Head Screws**.



Tighten all screws and set screws down before carefully mounting and wiring the TV and speaker. 2 people are needed for this task.

Questions? Call Customer Service at 1.888.213.5015, Mon-Fri 8AM-6PM EST



### QUESTIONS?

Call Customer Service 1.888.213.5015 Mon–Fri 8AM–6PM EST

CALL 1.888.213.5015 OR VISIT WWW.LEONSPEAKERS.COM FOR MORE INFORMATION

ALL INFORMATION COPYRIGHT ©2016, LEON SPEAKERS, INC.