## Control4<sup>®</sup> Z-Wave<sup>®</sup> Module and USB Dongle



## Control4<sup>®</sup> Z-Wave<sup>®</sup> Module and USB Dongle C4-ZWDUSB C4-ZWE/C4-ZWH/C4-ZWU

Paired with the Control4 Z-Wave Module and USB Dongle, the EA Series controllers are now Z-Wave Plus<sup>™</sup> certified and designed to augment Control4 lighting, comfort, and security solutions with supported Z-Wave devices. Native Z-Wave support includes water sensors, in-wall power outlets, door and window sensors, and shade control. For a list of supported Z-Wave products, please visit ctrl4.co/z-wave. Available drivers for supported Z-Wave products are available in the Online Driver Database.

The USB Dongle plugs into the USB port of an EA controller and allows the dealer the flexibility to mount the Z-Wave USB Module in an ideal location to optimize Z-Wave RF performance.

The Z-Wave Module is available in three models to support regions throughout the world:

- Region U
- Region E
- Region H

To see which version of the module is required in your particular country, see the table on the last page or visit <u>ctrl4.co/z-wave</u>.















## Control4<sup>®</sup> Z-Wave<sup>®</sup> Module and USB Dongle

Z-Wave USB Dongle			
Model number	C4-ZWDUSB		
Power			
Power requirements	Powered by USB, no power supply required		
	Other		
Mounting	1 wall-mount slot on the bottom of the dongle Do not mount on a metal surface!		
Cable	Includes 1-meter USB cable		
Operating temperature	14° - 185°F (-10° - 85°C)		
Dimensions (H x W x D)	1" (25.8 mm) x 2.4" (62 mm) x 1.6" (40 mm)		
Shipping weight	.12 lbs (.05 kg)		
	Optional accessories		
3-Meter USB Cable	C4-USB-WH		

Z-Wave Module		
Model numbers	C4-ZWE (Region E) C4-ZWH (Region H) C4-ZWU (Region U)	
Power		
Power requirements	No power required. Powers from the Z-Wave USB Dongle (C4-ZWDUSB)	
Other		
Installation	Installs into the Z-Wave USB Dongle.	
Operating temperature	14° - 185°F (-10° - 85°C)	
Dimensions (H x W x D)	.5" (13.1 mm) x .8" (20.2 mm) x .77" (19.6 mm)	
Shipping weight	<.01 lbs (.005 kg)	

Important! Each Z-Wave module operates on different frequencies, use the tables on the next page to find the appropriate module for your region. For more information, visit <u>ctrl4.co/z-wave</u>.

For more information on supported Z-Wave devices, Z-Wave frequencies, and Z-Wave setup documentation, visit ctrl4.co/z-wave





Copyright ©2016, Control4 Corporation. All rights reserved. Control4, the Control4 logo, the 4-ball logo, 4Store, 4Sight, Control4 My Home, and Mockupancy are registered trademarks or trademarks of Control4 Corporation in the United States and/or other countries. The Z-Wave trademark and logo are owned by Sigma Designs, Inc. All other names and brands may be claimed as the property of their respective owners. All specifications subject to change without notice. DOC-00238-A 09-01-2016 DH



## Z-Wave Module frequencies

Region E Module (C4-ZWE)		
Country	Frequencies	
CEPT*	868.4, 869.85MHz	
China	868.4MHz	
French Guiana	868.4, 869.85MHz	
India	865.2MHz	
Indonesia	868.4, 869.85MHz	
Russia	869.0MHz	
Singapore	868.4, 869.85MHz	
South Africa	868.4, 869.85MHz	
UAE	868.4, 869.85MHz	
Malaysia	868.1MHz	

\*CEPT is the European regional organisation dealing with postal and telecommunications issues and presently has 45 Members: Albania, Andorra, Austria, Azerbaijan, Belarus, Belgium, Bosnia and Herzegovina, Bulgaria, Croatia, Cyprus, Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Liechtenstein, Lithuania, Luxembourg, Malta, Moldova, Montenegro, Monaco, Netherlands, Norway, Poland, Portugal, Romania, Russian Federation, San Marino, Serbia, Slovakia, Slovenia, Spain, Sweden, Switzerland, The former Yugoslav Republic of Macedonia, Turkey, Ukraine, United Kingdom, and Vatican.

Region H Module (C4-ZWH)			
Frequencies			
919.8, 921.4MHz			
919.8, 921.4MHz			
922.5, 923.9, 926.3 MHz			
919.8, 921.4MHz			
919.8MHz			
922.5, 923.9, 926.3MHz			
919.8, 921.4MHz			
919.8, 921.4MHz			
922.5, 923.9, 926.3MHz			
919.8, 921.4MHz			
919.8, 921.4MHz			
920.9, 921.7, 923.1MHz			

Region U Module (C4-ZWU)			
Country	Frequencies		
Aruba	908.4, 916MHz		
Bahamas	908.4, 916MHz		
Barbados	908.4, 916MHz		
Bermuda	908.4, 916MHz		
Bolivia	908.4, 916MHz		
British Virgin Islands	908.4, 916MHz		
Canada	908.4, 916MHz		
Cayman Islands	908.4, 916MHz		
Chile	908.4, 916MHz		
Colombia	908.4, 916MHz		
Ecuador	908.4, 916MHz		
Guatemala	908.4, 916MHz		
Honduras	908.4, 916MHz		
Israel	916MHz		
Jamaica	908.4, 916MHz		
Mexico	908.4, 916MHz		
Nicaragua	908.4, 916MHz		
Panama	908.4, 916MHz		
St Kitts & Nevis	908.4, 916MHz		
Suriname	908.4, 916MHz		
Trinidad & Tabago	908.4, 916MHz		
Turks & Caicos Islands	908.4, 916MHz		
USA	908.4, 916MHz		



