

3G ULTRA Warp Engine Transmitter

VBS-HDIP-737POE

Just Add
Power



Viewing Video from a Different Angle

The 3G Ultra Warp Engine Transmitter rotates any video signal in 0.1° degree increments.

A single Warp Engine Transmitter can build a full Artistic Video Wall with displays rotated at any angle and the ability to show any source in the system!

The Warp Engine Transmitter is fully compatible with all 3G Ultra installations. Add a single Warp Engine to provide rotation to all displays. Multiple Warp Engines can be combined to produce more complex Artistic Video Walls.

Features

Artistic Video Wall

Create, build and watch your new video wall come to life with the ability to rotate your displays up to 360 degrees.

Image Pull

Provides a more powerful user experience giving the control system the capability of displaying a preview image inside the user interface

Scalability

Fully compatible with all 3G Ultra Products

Video Rotation

Rotate any HDMI source in a Just Add Power matrix in 0.1° degree increments

Rotate your video up to 360° degrees

Any video input from 3G system

New, rotated video output

3G ULTRA Warp Engine Transmitter

VBS-HDIP-737POE

Just Add
Power

Front of Device:



All measurements in millimeters (mm)

Back of Device:



All measurements in millimeters (mm)

Specifications

Bandwidth	Up to 600 Mbps	POE	20 watts maximum
Compliance	HDCP 2.2 & RoHS/FCC/CE	Ports	2 x Gigabit Ethernet
Dimensions & Weight	220x44.5x124m/8.66x1.75x4.88inch (19-inch rack, 1 RU with wings) 0.64 kg / 1.4 lb	Power Supply (not included)	DC12V, 2A minimum 5.5mm/2.1 mm, Positive tip
Encryption	Hardware-Based AES 256-bit Encryption of Network Video Signal	Supported Video & Audio	Up to 4096x2160 Uncompressed multi-channel audio
Operating Temp	0-60 °C / 32-140 °F		